

COMMANDER LE CLEF'S Secret Encoder Wheel



F Press **SHIFT** - **NEW LINE** - Cursor changes to **F**

E Press **SHIFT** - **SYMBOL** - Cursor changes to **E**

Keyword ZX81 Spectrum Keyword ZX81 Spectrum

ABS	F G	E G
ACS	F S	E SHIFT -W
AND	SHIFT -2	SYMBOL -Y
ASN	F A	E SHIFT -Q
AT	F C	SYMBOL -I
ATN	F D	E SHIFT -E
ATTR		E SHIFT -L
BEEP		E SHIFT -Z
BIN		E B
BORDER		B
BREAK	SPACE	SHIFT - SPACE
BRIGHT		E SHIFT -B
CAT		E SYMBOL -9
CHRS	F U	E U
CIRCLE		E SHIFT -H
CLEAR	X	X
CLOSE#		E SYMBOL -5
CLS	V	V
CODE	F I	E I
CONT	C	C
CONTINUE		C
COPY	Z	Z
COS	F W	E W
DATA		E D
DEF FN		E SYMBOL -1
DELETE		SHIFT -0
DIM	D	D
DRAW		W
EDIT	SHIFT -1	SHIFT -1
ERASE		E SYMBOL -7
EXP	F X	E X
FAST		
FLASH	SHIFT -F	
FN		E SHIFT -V
FOR		E SYMBOL -2
FORMAT	F	F
		E SYMBOL -0
GOSUB	H	H
GOTO	G	G
GRAPHICS		SHIFT -9
IF	U	U
IN		E SHIFT -I
INK		E SHIFT -X
INKEY\$	F B	E N
INPUT	I	I
INT	F R	E R
INVERSE		E SHIFT -M
LEN	F K	E K
LET	L	L
LINE		E SYMBOL -3
LIST	K	K
LLIST	SHIFT -G	E V
LN	F Z	E Z
LOAD	J	J
LPRINT	SHIFT -S	E C
MERGE		E SHIFT -T
MOVE		E SYMBOL -6
NEW	A	A
NEXT	N	N
NOT	F N	SYMBOL -S

OPEN#		E SYMBOL -4
OR	SHIFT -W	SYMBOL -U
OUT		E SYMBOL -0
OVER		E SHIFT -N
PAPER		E SHIFT -C
PAUSE	M	M
PEEK	F O	E O
PI	F M	E M
PLOT	Q	Q
POINT		E SYMBOL -8
POKE	O	O
PRINT	P	P
RAND	T	T
RANDOMIZE		E A
READ	E	E
REM		E S
RESTORE	Y	Y
RETURN	F T	E T
RND	R	R
RUN		S
SAVE	S	E SHIFT -K
SCREEN\$		E F
SCROLL	B	E Q
SGN	F F	
SIN	F Q	
SLOW	SHIFT -D	E H
SQR	F H	SYMBOL -D
STEP	SHIFT -E	SYMBOL -A
STOP	SHIFT -A	E Y
STR\$	F Y	
TAB	F P	E P
TAN	F E	E E
THEN	SHIFT -3	SYMBOL -G
TO	SHIFT -4	SYMBOL -F
UNPLOT	W	E L
USR	F L	
VAL	F J	E J
VAL\$		E SHIFT -J
VERIFY		E SHIFT -R
<	SHIFT -N	SYMBOL -R
>	SHIFT -M	SYMBOL -T
=	SHIFT -L	SYMBOL -L
<=	SHIFT -R	SYMBOL -Q
>=	SHIFT -Y	SYMBOL -E
<>	SHIFT -T	SYMBOL -W

```

100 PRINT "ENCODE OR DECODE?"
110 INPUT M$
120 LET
    D$="ABCDEFGHIJKLMNOPQRSTUVWXYZ"
130 LET
    E$="ZXHAFOTERBLSINCWYQFJDMVGVUK"
140 IF M$(1)="E" THEN GOTO 200
150 LET A$=D$
160 LET D$=E$
170 LET E$=A$

200 PRINT "TEXT?"
210 INPUT T$
220 LET B$ = ""
230 FOR I=1 TO LEN (T$)
240 LET A$=T$(I)
250 FOR L=1 TO LEN (D$)
260 IF A$=D$(L) THEN GOTO 290
270 NEXT L
280 GOTO 300
290 LET A$=E$(L)
300 LET B$=B$+A$
310 NEXT I
320 PRINT B$
    
```

Keyword ZX81 Spectrum

"	SHIFT -P	SYMBOL -P
'		SYMBOL -7
\$	SHIFT -U	SYMBOL -4
*	SHIFT -B	SYMBOL -B
**	SHIFT -H	
+	SHIFT -K	SYMBOL -K
-	SHIFT -J	SYMBOL -J
,	SHIFT -.	SYMBOL -N
.		SYMBOL -M
:	SHIFT -Z	SYMBOL -Z
;	SHIFT -X	SYMBOL -O
/	SHIFT -V	SYMBOL -V
?	SHIFT -C	SYMBOL -C
!		SYMBOL -1
(SYMBOL -8
)	SHIFT -I	SYMBOL -9
[SHIFT -O	E SHIFT -Y
]		E SHIFT -U
{		E SHIFT -F
}		E SHIFT -G
@		SYMBOL -2
#		SYMBOL -3
%		SYMBOL -5
&		SYMBOL -6
\		E SHIFT -D
		E SHIFT -S
~		E SHIFT -A
£	SHIFT - SPACE	SYMBOL -0
©		SYMBOL -X
"	SHIFT -Q	E SHIFT -P
**	SHIFT -H	
←	SHIFT -5	SHIFT -5
↓	SHIFT -6	SHIFT -6
↑	SHIFT -7	SHIFT -7
→	SHIFT -8	SHIFT -8
↑		SYMBOL -H

